

EAS Anti-theft Self Alarm Spider Wrap



Anti-theft self alarm spider wrap is an EAS tag with magnetic and alert frequency. It has four extendable and length adjustable security cables, suitable for all types of boxed merchandise. It will trigger the alarm as common tags when the spider tag is near the EAS system. Besides, it will also immediately alarm even not near the anti-theft system when the cables on the products is cut, as there is built-in button battery and mini alarm in this spider tag. With this self alarm spider tag, it can give dual or triple protection for your merchandise.



FEATURES

- Exquisite & elegant design.
- Super fast 5s cable winding up.
- Rugged enclosure against 1min knocking.
- High performance with lower power consumption.
- Extremely low probability of self-lock.

TECHNICAL SPECIFICATION

			
Model	SW100	SW200	SW300
Frequengy	8.2mhz/58Khz	8.2mhz/58Khz	8.2mhz/58Khz
Spec	Dual alarm	Dual alarm	Dual alarm/Triple alarm
Dimension	50*33mm	70*33mm	73*52mm
Color	Black or customized	Black or customized	Black or customized
Lock	Normal/Super	Normal/Super	Normal/Super
Cable length	650mm or customized	900mm or customized	800mm or customized
Battery life	3-5years	3-5years	3-5years
Consumption	30mAh/Per year	30mAh/Per year	25mAh/Per year
Automatically disalarm	Stop alarming in 2h	Stop alarming in 2h	Stop alarming in 5min
Pulling force	≥350N	≥350N	≥500N
Pressure force	≥650N	≥650N	≥800N
Lanyard coat	Nylon	Nylon	Nylon
Instantaneous Force	15KG	15KG	25KG
Buzzer db	95db	95db	95db
Low battery reminder	Didi" sound remind	Didi" sound remind	LED flash
Package	250pcs/carton 13.8kg	100pcs/carton 9kg	100pcs/carton 9kg
Detection distance	1.5-1.7meter	1.7-1.9meter	1.7-1.9meter

USER GUIDE

- After getting the spider tag, twist it in the opposite direction indicated by the arrow to release the protection cables.
- Put the goods in a mesh bag, and make four protection cables be evenly distributed around the goods.
- Tighten the protection cables in the direction indicated by the arrow (just fit the package), then press the button, and the label will start to work.
- After finishing the installation, the goods should be placed in the correct way to avoid damage to the goods, and achieve a good effect of protection.
- After customers purchase the goods, the clerk can use detacher and press the button again to open the spider tag, then it will stop working (if the goods is released by cutting the cables, an alarm will be triggered).



Dongguan Lifangmei Electronic Technology Co., Ltd

Email: sales@lifmei.com | Whatsapp: +8613688916156

Website: www.emenotec.com

Add:No.4, Industrial Road 2nd , Liyatang ,Tangxia Town, Dongguan, Guangdong